



SS24

24-Channel Programmable Dimming Controller



5 Holt Drive
Stony Point, NY 10980
845-947-3034
tslight.com

Dimensions & Weight

- **Dimensions:** 13" (L) x 21" (W) x 5" (H)
- **Weight:** 10 lbs.

Take your shows to the next level with the SS24. This 24 channel dimming console will give you the power to create the light show of a lifetime. Tying in your audio and visual production, the scene setter incorporates a line level input that will synchronize the music with your par can lights while also allowing for individual adjustment to each of your pars with its 24 adjustable channel faders. With up to 11,000 programmable scenes and 48 programmable chases (all password protected) and 1,000 scenes per chase, you can rest easy that your unique set-up is kept secure while it runs 12 chases simultaneously. Adjust your fixtures in either percentage or DMX value to achieve the dimming intensity that you desire. With its low weight and bright display, you'll have no trouble moving this controller where it's needed and getting it set up in no time. Master your entire entertainment system with the SS24 DMX Dimming Console, and create a light show your crowd won't forget.

SS24 is a 24 Channel Dimming Console for the purpose of managing the levels of your conventional light entertainment system. With lots of built-in reprogrammable scenes and chases, you can quickly and easily create and manage your light show. This portable control system is perfect for live entertainment stages, mobile DJ's, clubs, bars or for any professional event that requires conventional dimming control of 24 channels or less.

Features

- 24 channel conventional dimming console
- Two scene operation (A/B faders)
- 11,000 programmable scenes- password protected
- 48 programmable chases (stacks)- password protected
- Up to 1,000 scenes (steps) per chase
- 12 x 4 Pages = 48 total chases
- Solo & Pile On chase operation
- Blind & Dark functions
- 24 individual channel faders
- 24 bump buttons
- Tap Sync button for chase speed / fade override
- Independent speed & fade control
- Full-On button for 100% momentary output to all 24 channels
- Bright LCD display
- Use in conjunction with the ADJ or Elation: DP-DMX20L, CYBER PAK, UNI PAK-II, UNI BAR, DP-415, DP-640, RMD620 & RMD1210
- Line level audio input and built in microphone for music sync operation
- Audio level fader
- Fog Machine input and trigger button-compatible with ADJ Vaporizer, MB-1000, Stallion, Vapor- Flow, Fog Storm-1200 & 1700
- DMX Polarity switch (2-, 3+, / 2+, 3-)
- Midi In, Out & Thru connectors
- **Power:** 120V / 12V DC, 500mA. (Included)
*Also available in 220V