

# CYX, CYP & CYCR FLUSH MOUNT INSTALLATION INSTRUCTIONS

electrical box: provided 1' fixture wires to the feed wires in the With the yellow wire nuts provided, attach the

to hang below the box as shown. to [-] (usually grey). Allow only the fixture wires dimming, VIOLET to [+] (usually violet) & GREY GREEN to GROUND, and, if required for 0-10 BLACK to HOT, WHITE to NEUTRAL




provided 8-32 x 3/4 screws canopy to the electrical box with the canopy nipple as shown and attach the Insert the fixture wires through the



# STEP 4:

LED/driver assembly onto the nipple as shown.



# STEP 3:


STEP 5:

fixture wire to the appropriate wire in the LED/driver With the blue wire nuts provided, connect each


assembly:

BLACK to BLACK (or BROWN) from driver, WHITE

Turning counter-clockwise, carefully unscrew the cylinder from the LED/driver assembly as shown, and set the cylinder aside.



Turning clockwise, carefully thread the



and, if required for 0-10 dimming, VIOLET to VIOLET to WHITE (or BLUE) from driver, GREEN to GREEN

from driver & GREY to GREY from driver.

onto the LED/driver assembly as shown. Make STEP 6: certain not to cross thread the 2 parts! Turning clockwise, carefully thread the cylinder

